

EZ Tower Light



Features:


- Easy deployment, configure functions via a software template eliminates the need to program tower light functions in ladder logic.
- Make your status system easier to understand by leveraging the multi-color LEDs which allows the flexibility to control 4 colors and 2 flash rates per unit
- A single product for a wide range of customers
- USB installation simplifies wiring

PFXZCETWHA1	PFXZCETWW1
EZ Tower Light tube mounting with fixing plate	EZ Tower Light with base mounting
GP-Pro EX Ver. 3.6 or later	
SP5000, GP4000 Series, GP4000M Modular HMI Series*, LT4000M, Except GP4100	
	EZ Tower Light tube mounting with fixing plate GP-Pro EX Ver. 3.6 or later SP5000, GP4000 Series, GP4000M

 * When you connect with GP4000M Series, please connect via self power USB Hub.


Model	PFXZCETWHA1	PFXZCETWW1	
Description	EZ Tower Light tube mountingwith fixing plate	EZ Tower Lightwith base mounting	
Certifications	UL 508, cUL, CSA22.2, CE	1	
Color	Red / Green / Blue / Yellow		
Light Mode	Off / On / Blink (High) / Blink (Low)		
Buzzer	4 sounds		
Buzzer Volume	High / Middle / Low		
Buzzer Tone	High / Low		
Buzzer	85dB	82dB	
Interface	USB 2.0 (Mini B)		
Supply Voltage	DC 5V (Powered from USB bus)		
Power Consumption	2W		
Surrounding Air Operating Temperature	0 to 55 ° (32 to 131 °		
Operating Humidity	35 to 85%RH (no condensation)		
Operating Atmosphere	No Corrosive Gas		
Storage Temp.	-35 to 70 (-95 to 158)		
Protection	IP54		
Weight	0.3kg (0.66lb)		





Part Number	Description
PFXCETWW1	EZ Tower Light with base mounting
PFXZCETWHA1	EZ Tower Light tube mounting with fixing plate

Options		
Part Number	Description	
ZC9USCBMB1	Cable for connecting from an EZ Tower Light to a Pro-face's interface unit.	
XVGUZ02*	Cable lock to prevent disconnection of USB cable	
*One piece is included	d with the EZ Tower Light unit.	



Pro-face America

Phone: 734.477.0600 Fax: 734.864.7347 www.profaceamerica.com Customer Service Hotline: 800.289.9266



